



## BC SERIES

BC SERIES	PEDESTAL ONLY LOW TO HIGH	BC SERIES	PEDESTAL + BC-PH5 (U-PH5) (BOTTOM SLOPE CORRECTOR + 9/16") LOW TO HIGH	BC SERIES	PEDESTAL + BC-PH5 (U-PH5) + KIT 2 (ADJUSTABLE JOIST HOLDER) LOW TO HIGH	BC SERIES	PEDESTAL + BC-PH5 (U-PH5) + INVERTER (C4-COUPLER) LOW TO HIGH
		(OR) PEDS+KIT5 FIXED JOIST HOLDERS+BC-PH5 (U-PH5) SLOPE CORRECTORS		USE LONG PLUG AND PIN TO ATTACH KIT-2 (+7/16")			
BC 0 (FIXED HEIGHT PEDESTAL)	7/16"	BC 0 (FIXED HEIGHT PEDESTAL) + BC-PH5 (U-PH5)	1"				
BC 1 (FIXED HEIGHT PEDESTAL)	9/16"	BC 1 (FIXED HEIGHT PEDESTAL) + BC-PH5 (U-PH5)	1-1/8"				
BC 0 (x2 STACKED)	3/4"	BC 0 (x2 STACKED) + BC-PH5 (U-PH5)	1-5/16"				
BC 1 + BC 0 (STACK+CONNECT)	1"	BC 1 + BC 0 (STACK+CONNECT) + BC-PH5 (U-PH5)	1-9/16"				
BC 0 (x3 STACKED)	1-1/16"	BC 0 (x3 STACKED) + BC-PH5 (U-PH5)	1-5/8"				
BC 02	1-1/8" to 1-9/16"	BC 02 + BC-PH5 (U-PH5)	1-11/16" to 2-1/8"	BC 02 + BC-PH5 (U-PH5) + KIT 2	2-1/8" to 2-9/16"		
BC 2	1-9/16" to 2-3/16"	BC 2 + BC-PH5 (U-PH5)	2-1/8" to 2-3/4"	BC 2 + BC-PH5 (U-PH5) + KIT 2	2-9/16" to 3-3/16"		
BC 3	2-3/16" to 3-3/8"	BC 3 + BC-PH5 (U-PH5)	2-3/4" to 3-15/16"	BC 3 + BC-PH5 (U-PH5) + KIT 2	3-3/16" to 4-3/8"		
BC 4	3-3/8" to 5-1/2"	BC 4 + BC-PH5 (U-PH5)	3-15/16" to 6-1/16"	BC 4 + BC-PH5 (U-PH5) + KIT 2	4-3/8" to 6-1/2"		
BC 5	4-9/16" to 7-7/8"	BC 5 + BC-PH5 (U-PH5)	5-1/8" to 8-7/16"	BC 5 + BC-PH5 (U-PH5) + KIT 2	5-9/16" to 8-7/8"		
BC 6 (BC 4 + x1 COUPLER)	7-13/16" to 12"	BC 6 (BC 4 + x1 COUPLER) + BC-PH5 (U-PH5)	8-3/8" to 12-9/16"	BC 6 (BC 4 + x1 COUPLER) + BC-PH5 (U-PH5) + KIT 2	8-13/16" to 13"		
BC 7 (BC 5 + x1 COUPLER)	8-7/8" to 14-1/4"	BC 7 (BC 5 + x1 COUPLER) + BC-PH5 (U-PH5)	9-7/16" to 14-13/16"	BC 7 (BC 5 + x1 COUPLER) + BC-PH5 (U-PH5) + KIT 2	9-7/8" to 15-1/4"		
BC 8 (BC 5 + x2 COUPLERS)	13-3/16" to 20-5/8"	BC 8 (BC 5 + x2 COUPLERS) + BC-PH5 (U-PH5)	13-3/4" to 21-3/16"	BC 8 (BC 5 + x2 COUPLERS) + BC-PH5 (U-PH5) + KIT 2	14-3/16" to 21-5/8"	BC 8-INV (BC 5 + x1 COUPLER + INV) + BC-PH5 (U-PH5)	14" to 18-7/8"
BC 9 (BC 5 + x3 COUPLERS)	17-1/2" to 27-1/8"	BC 9 (BC 5 + x3 COUPLERS) + BC-PH5 (U-PH5)	18-1/16" to 27-11/16"	BC 9 (BC 5 + x3 COUPLERS) + BC-PH5 (U-PH5) + KIT 2	18-5/8" to 28-1/8"	BC 9-INV (BC 5 + x2 COUPLERS + INV) + BC-PH5 (U-PH5)	17-3/4" to 25-3/8"
BC 10 (BC 5 + x4 COUPLERS)	21-13/16" to 27-3/8"	BC 10 (BC 5 + x4 COUPLERS) + BC-PH5 (U-PH5)	22-3/8" to 27-15/16"	BC 10 (BC 5 + x4 COUPLERS) + BC-PH5 (U-PH5) + KIT 2	22-13/16" to 28-3/8"	BC 10-INV (BC 5 + x3 COUPLERS + INV) + BC-PH5 (U-PH5)	22-11/16" to 32-1/2"
BC 11 (BC 5 + x5 COUPLERS)	26-1/8" to 33-3/4"	BC 11 (BC 5 + x5 COUPLERS) + BC-PH5 (U-PH5)	26-11/16" to 34-5/16"	BC 11 (BC 5 + x5 COUPLERS) + BC-PH5 (U-PH5) + KIT 2	27-1/8" to 34-5/8"	BC 11-INV (BC 5 + x4 COUPLERS + INV) + BC-PH5 (U-PH5)	28" to 38-9/16"
BC 12 (NO USE_200328)	30-7/16" to 46-1/8"	BC 12 (NO USE_200328) + BC-PH5 (U-PH5)	31" to 46-11/16"	BC 12 (NO USE_200328) + BC-PH5 (U-PH5) + KIT 2	31-7/16" to 47-1/8"	BC 12-INV (BC 5 + x5 COUPLERS + INV) + BC-PH5 (U-PH5)	31-3/8" to 45-1/16"

5-10% SLOPE: x2 BC-PH5 SLOPE CORRECTORS + x1 BC-1 + 1"

10-15% SLOPE: x3 BC-PH5 SLOPE CORRECTORS + x2 BC-1 + 2"

For Ramps: PH5 Top Slope Correctors add 3/8"

USE PIN TO ATTACH BC-1 TO BOTTOM SLOPE CORRECTOR; AND LONG PLUG AND PIN TO ATTACH TOP SLOPE CORRECTOR TO BC-1

BC-C3 COUPLER ADDS: 4-5/16" TO 6-3/8"