



BC SERIES

BC SERIES	PEDESTAL ONLY LOW TO HIGH	BC SERIES	PEDESTAL + BC-PH5 (U-PH5) (BOTTOM SLOPE CORRECTOR + 9/16") LOW TO HIGH	BC SERIES	PEDESTAL + BC-PH5 (U-PH5) + KIT 2 (ADJUSTABLE JOIST HOLDER) LOW TO HIGH	BC SERIES	PEDESTAL + BC-PH5 (U-PH5) + INVERTER (C4-COUPLER) LOW TO HIGH
		(OR) PEDS+KIT5 FIXED JOIST HOLDERS+BC-PH5 (U-PH5) SLOPE CORRECTORS		USE LONG PLUG AND PIN TO ATTACH KIT-2 (+7/16")			
U-TAB + U-PAD	1/8" to 3/8"						
BC 0 (FIXED HEIGHT PEDESTAL)	7/16"	BC 0 (FIXED HEIGHT PEDESTAL)	1"				
BC 1 (FIXED HEIGHT PEDESTAL)	9/16"	BC 1 (FIXED HEIGHT PEDESTAL)	1-1/8"				
BC 0 (x2 STACKED)	3/4"	BC 0 (x2 STACKED)	1-5/16"				
BC 1 + BC 0 (STACK+CONNECT)	1"	BC 1 + BC 0 (STACK+CONNECT)	1-9/16"				
BC 0 (x3 STACKED)	1-1/16"	BC 0 (x3 STACKED)	1-5/8"				
BC 02	1-1/8" to 1-9/16"	BC 02	1-5/8" to 2-1/8"	BC 02	2-1/16" to 2-9/16"		
BC 2	1-9/16" to 2-3/16"	BC 2	2-1/8" to 2-11/16"	BC 2	2-9/16" to 3-1/8"		
BC 3	2-3/16" to 3-3/8"	BC 3	2-11/16" to 3-7/8"	BC 3	3-1/8" to 4-5/16"		
BC 4	3-3/8" to 5-1/2"	BC 4	3-7/8" to 6-1/16"	BC 4	4-5/16" to 6-1/2"		
BC 5	4-9/16" to 7-7/8"	BC 5	5-1/8" to 8-7/16"	BC 5	5-9/16" to 8-7/8"		
BC 6 (BC 4 + x1 COUPLER)	7-13/16" to 9-7/16"	BC 6 (BC 4 + x1 COUPLER)	8-3/8" to 10"	BC 6 (BC 4 + x1 COUPLER)	8-13/16" to 10-7/16"		
BC 7 (BC 5 + x1 COUPLER)	9-1/16" to 14-3/16"	BC 7 (BC 5 + x1 COUPLER)	9-5/8" to 14-3/4"	BC 7 (BC 5 + x1 COUPLER)	10-1/16" to 15-3/16"		
BC 8 (BC 5 + x2 COUPLERS)	13-7/16" to 18-5/16"	BC 8 (BC 5 + x2 COUPLERS)	14" to 18-7/8"	BC 8 (BC 5 + x2 COUPLERS)	14-7/16" to 19-5/16"	BC 8 (BC 5 + x2 COUPLERS + INVERTER)	14" to 18-7/8"
BC 9 (BC 5 + x3 COUPLERS)	17-13/16" to 24-13/16"	BC 9 (BC 5 + x3 COUPLERS)	18-3/8" to 25-3/8"	BC 9 (BC 5 + x3 COUPLERS)	18-13/16" to 25-13/16"	BC 9 (BC 5 + x3 COUPLERS + INVERTER)	17-3/4" to 25-3/8"
BC 10 (BC 5 + x4 COUPLERS)	22-1/8" to 31-5/16"	BC 10 (BC 5 + x4 COUPLERS)	22-11/16" to 31-7/8"	BC 10 (BC 5 + x4 COUPLERS)	23-1/8" to 32-5/16"	BC 10 (BC 5 + x4 COUPLERS + INVERTER)	22-11/16" to 32-1/2"
BC 11 (BC 5 + x5 COUPLERS)	26-7/16" to 38"	BC 11 (BC 5 + x5 COUPLERS)	27" to 38-9/16"	BC 11 (BC 5 + x5 COUPLERS)	27-1/16" to 39"	BC 11 (BC 5 + x5 COUPLERS + INVERTER)	28" to 38-9/16"
BC 12 (NO USE_200328)	30-13/16" to 44-1/2"	BC 12 (NO USE_200328)	31-5/16" to 45-1/16"	BC 12 (NO USE_200328)	31-3/4" to 45-1/2"	BC 12 (NO USE_200328 + INVERTER)	31-3/8" to 45-1/16"

5-10% SLOPE: x2 BC-PH5 SLOPE CORRECTORS + x1 BC-1 + 1"

10-15% SLOPE: x3 BC-PH5 SLOPE CORRECTORS + x2 BC-1 + 2"

For Ramps: PH5 Top Slope Correctors add 3/8"

USE PIN TO ATTACH BC-1 TO BOTTOM SLOPE CORRECTOR; AND LONG PLUG AND PIN TO ATTACH TOP SLOPE CORRECTOR TO BC-1

BC-C3 COUPLER ADDS: 4-5/16" TO 6-3/8"